

# hAP lite

The home Access Point lite (hAP lite) is an ideal little device for your apartment, house or office.

It supports button triggered WPS, for the convenience of not typing a complicated password when somebody wants to have wireless internet access, and can also be told to change to cAP mode and join a CAPsMAN centrally managed network by the push of a button.

Of course, the device runs RouterOS with all the features, bandwidth shaping, firewall, user access control and many others.

The hAP lite is equipped with a powerful 650MHz CPU, 32MB RAM, dual chain 2.4GHz onboard wireless, four Fast Ethernet ports and a RouterOS L4 license. USB power supply is included.



Power adapter

Order code	RB941-2nD
CPU	QCA9533 650MHz CPU
Memory	32MB DDR RAM
Ethernet	4x 10/100 Mbit/s Ethernet with Auto-MDI/X
Wireless cards	Onboard dual chain 2.4GHz 802.11b/g/n QCA9533 wireless module; 10kV ESD protection on each RF port, WPS support via button
Extras	Reset switch
LEDs	Power LED, 4x Ethernet LED, user LED
Power input	Packaged with 5V DC 0.7A power adapter
Dimensions	113x89x28mm
Max consumption	3W at 5V
Operating Temp	-20C .. +70C tested
OS	MikroTik RouterOS, Level 4 license (AP support)

TX/RX at 1Mbps	22dBm / -96dBm
TX/RX at 11Mbps	22dBm / -89dBm
TX/RX at 6Mbps	20dBm / -93dBm
TX/RX at 54Mbps	18dBm / -74dBm
TX/RX at MCS0	20dBm / -93dBm
TX/RX at MCS7	16dBm / -71dBm
Antenna	1.5dBi gain